



The 8-button transmitter FRT-HS 8 is a handheld unit for RF transmission of up to 8 commands, which can be received and indicated visually and/or by tone or which can switch up to 8 relays. The 8 buttons can either be imprinted with „F1“ ... „F8“ or can be blank, having two detachable strips for an individual inscription.

The handheld unit contains a RF-transceiver for SRD-Band 869 MHz for licence free operation within the EU, a control-LED to indicate both, the transmission activity and the technical call acknowledgement by the receiving unit. In case that this should fail, one or even a second call repetition is initiated automatically.

A rotary switch inside the battery compartment is used for setting the address of the 8-button transmitter, being preset to “1”. For use of multiple transmitters in the same premise, it can be set to “1” ... “9”, enabling the individual receiver unit (pager or call indication panel) to recognize, which particular transmitter had sent the call.

### Technical data:

Dimensions: ca. L105 x B58 x H19mm  
Protection class: IP 40, ABS  
Weight: ca. 50g  
Power supply: battery 2 x 1,5V, Type AAA, Alkali-Mangan

### Options:

Clip to be screwed at the back  
Holder for wall mounting of the transmitter with clip

### Selection of matching receivers:

FRT-RX-2 Receiver for 2 commands, each with 1 relay  
FE-8 RG Receiver unit with 8 relays  
FRT-8 N Receiver unit with numeric display (1 ... 8)  
FRT-32 Touch Call indication touch panel (1 ... 16/32)  
MP-U3 Mobile wrist watch pager with vibration and alphanumeric LCD  
MP-T3 Mobile pocket pager with vibration, tone and alphanumeric LCD